

### **Terminal Help Desks:**

Paymentech 800-782-1266

First Data Nashville: 800-542-1894

TSYS: 800-847-2737

APRIVA (Wireless Terminals): 866-277-4828

### **FD130 (UNITY)**

Press Orange Wrench Icon at Top Right on-screen (terminal has touchscreen)

Select Date/Time

Enter Date MM/DD/YYYY

Enter Time HH/MM/SS (Military time)

Press Enter then the red Cancel key

### **FD130 (Before UNITY)**

Press 6 or tap SYSTEM on screen

Press 5 or tap Date/Time on screen

DATE/TIME CORRECT? Press 6 or tap No on screen

Use arrow key (above red key) to select hour, minute, seconds field, press Backspace (yellow button) to clear and input correct values.

### **FD100, FD200, FD300**

Press 6 or tap SYSTEM on screen (these models also support touchscreen)

Press 5 or tap Date/Time on screen

DATE/TIME CORRECT? Press 6 or tap No on screen

Type in correct values. Press Alpha then the key to make the colon. (You press alpha first on FD machines)

### **Vx520 First Data**

Press 0 for System, then 3 for Date-Time (Vx does not support touchscreen)

### **Vx520 Terminals (Chase)**

Press the purple scroll button until you see Other Setup. Select that option with the F key next to it. The terminal will prompt for password. Type in 1, Alpha, Alpha, 6, 6, 8, 3, 1, and then Enter. (no commas of course). From the Setup menu scroll until you see Time/Date menu option and choose it with the Fkey next to it. When you see MMDDYYYY type in the correct date and/or press Enter, then change Time and press Enter.

### **Vx510, Vx570 Terminals**

Press the purple scroll button until you see Other Setup. Select that option with the F key next to it. The terminal will prompt for password. Type in 1, Alpha, Alpha, 6, 6, 8, 3, 1, and then Enter. (no commas of course). From the Setup menu scroll until you see Time/Date menu option and choose it with the Fkey next to it. When you see MMDDYYYY type in the correct date and/or press Enter, then change Time and press Enter.

### **Hypercom T7 Terminals**

Press the blue Function key, 10, Enter. If it asks for password, it's "0000", Enter.

This will prompt you for the Time and Date so that you can change it. Pressing Enter makes the changes that you specify. Once it's reset you can press the red Cancel key to return to default swipe card screen.

### **Hypercom Optimum T4xx Terminals**

Press the blue Function key, then 10, then Enter. It will ask for password, this is "0000", Enter.  
You will then be asked to key the date in dd/mm/yy format. Then key the time in military format.

### **Ingenico ICT250 Terminals:**

From the idle screen, press the F key

You will need to put in the SYSTEM MANAGER Password:

CPS2468

To make alpha characters you'll press the number and then F to change it. It is case sensitive I believe so use caps.

Then from the FUNCTIONS menu, choose TELUM MANAGER, or option 0

Then choose option 3, INITIALIZATION.

Then choose option 1, PARAMETERS

Your top choice will then be Date and Time. That menu will let you make the changes.